

Marinelec Lynx V3S Watch Alarm

User Manual

When power is applied the device beeps and flashes lights.

Turn on by pressing the lower right hand button 'on/off'.

Set the time until first alarm by pressing the 'set' button to decrease the time delay down from 12 mins to a minimum of 3 mins. Stop pressing the 'set' button to select the time period.

Turn the key switch to **lock** to stop the man on watch from turning off or altering the countdown period.

When the device is 'on' and key switch is set to 'lock', the 'set' button toggles the brightness between bright and dim, and the 'on/off' button is a momentary test of the leds and internal buzzer, and of course the 'reset' button resets the countdown timer. As the time counts down the minutes left are shown visibly against the numbers 01 – 12.

Once the time period has elapsed, the reset button led flashes for 15 secs, after that the internal buzzer beeps for 3 mins, after which the external siren is triggered.

